# 78823 WI-FI VIDEO SCOPE USER GUIDE **STEELMAAN® 7770**





## TABLE OF CONTENTS

Overview	1
Product Description	1
Applications	1
Technical Data	1
Component Overview	2
Wi-Fi Video Scope Hardware Set-up	2
Android <sup>™</sup> Phone and Tablet Software Setup	3
iPhone and iPad Software Setup	4
PC Software Setup	5
Using the Steelman PRO Wi-Fi Video Scope - Mobile Devices	6
Camera Selection Page	6
Camera Preview Page	6
Viewing and Sharing Saved Images and Videos	7
Software Settings	9
Using the Steelman PRO Wi-Fi Video Scope - Windows	10
Camera Selection Page	10
Camera Preview Page	10
Viewing and Sharing Saved Images and Videos	11
Software Settings	11

## Overview

### **Product Description**

The Steelman PRO Wi-Fi Video Scope is a portable, hand-held, multifunctional inspection camera featuring and ultra-compact 5.5mm diameter camera and a high quality digital sensor that provides crystal clear video output. The camera connects via Wi-Fi to most smart devices and PCs for convenient viewing on any size screen. Using the included app, video, still images, and sound can be recorded, saved, and shared. Up to 5 viewing devices may be connected to the Wi-Fi at one time.

### **Applications**

The Steelman PRO Wi-Fi Video Scope has many potential applications, including, but not limited to:

- Automotive repair and maintenance
- Inspection of hard to reach or hard to see areas on vehicles, equipment, and structures
- Plumbing and construction
- Heating and air conditioning repair

NOTE: This product is not intended for medical use.

### **Technical Data**

Description	Data
Network Standard	IEEE 802.11 b/g/n
Antenna	Built in IPEX antenna
Operating Frequency	2.4 GHz
Date Rate	802.11 a/b/g/n up to 150 Mbps
Camera Diameter	5.5mm
Shaft Length	1 meter
Video Resolution	640x480
Viewing Angle	60°
Depth of Field	60-100mm
Camera Light Source	6 adjustable high intensity LEDs
Water/Dirt Resistance	IP67 certified
LED Flashlight	1 CREE LED
Operating Temperature	32° to 113°F (0° to 45°C) 802
Power Source	4x AA batteries
Max Battery Life	2-3 hours continuous use

## Wi-FI Video Scope Set Up

### **Component Overview**



### Wi-Fi Video Scope Hardware Set-up

- 1. Open battery compartment by sliding battery door down
- 2. Insert 4 AA alkaline batteries, making sure to insert correctly according to polarity
- 3. Attach camera shaft by twisting barrel connector clockwise
- 4. If you wish to use the device holder, slide the device holder into the bracket on top of the scope until it clicks and locks
- 5. Press the POWER button

### Android<sup>™</sup> Phone and Tablet Software Setup

- Open Google Play<sup>™</sup> store and search for "Steelman PRO Video Scope"
- Download and install app
- On your Android<sup>™</sup> device, open the Settings page
- From the Settings page, select "Wi-Fi Settings"
- Press the "Search" button to scan for Wi-Fi networks
- Select the "Steelman\_PRO\_Video\_Scope" network
- Connect to the network and enter the password "00000000"
- Start the Steelman PRO Wi-Fi Video scope application







Wi-Fi Connection Screen

### iPhone and iPad Software Setup

- Open iTunes Store and search for "Steelman PRO Video Scope"
- Download and install app
- On your iPhone or iPad open the Settings page
- From the Settings page, select "Wi-Fi Settings"
- Select the "Steelman\_PRO\_Video\_Scope" network
- Connect to the network and enter the password "00000000"
- Start the Steelman PRO Wi-Fi Video scope application

••• AT&T 穼	4:12 PM	<b>1</b> 🕉 🕷 🗖	••••• A	т&т 🤊	î		4:12	2 PM			10	* =
Settings	Wi-Fi		K Se	tting	S		Wi	-Fi				
				Wi-F	i							
Wi-Fi			~	JS P	roduc	ets				ļ	• <del>?</del>	1
Steelman_PR	O_Video_Scope	<b>a ≈</b> (i)		ľ		-	-		-	-		
CHOOSE A NETWORK			СНОС	IS	E Ste"	inter t elmai	the pan n_PR	assw D_Vid	ord fo eo_S	or cope	(	(f)
JS Products		<b>≜ ≈ (i</b> )		JS	[		,				(;	() ()
JS Products (	Guest	<b>∻</b> (i)		Ste	••••	••••					(:	(i)
JS Products I	т	<b>₽ 奈 (j</b> )		Othe	er	ancei			Joir	l I		
Other												
			Ask	to J	oin N	etworl	ks					
Ask to Join Netwo	orks	$\bigcirc$	Know	/n net orks a	works are ava	will be j ilable, y	ioined a rou will	automa have t	atically. o manu	. If no k ually se	nown lect a	
Known networks will k networks are available network.	be joined automatically a, you will have to mar	y. If no known wally select a	1	2	3	4	5	6	7	8	9	6
						$\square$						
			_	1	:	;		)	\$	&	@	_
			#+=			,	?	<u>`</u>	!	'		$\propto$
			ABC	¢	€		esp	acio			intr	0
Wi-Fi S	Settings Sc	reen	V	Vi-	Fi C	onn	ect	ion	Scr	een		

Wi-Fi Connection Screen

### PC Software Setup

- Open web browser and go to www.steelmanpro.com/downloads. Select "Wi-Fi Video Scope"
- From the Wi-Fi Video Scope page, click on "Download Software"
- Once the file has completed downloading, click "run". Follow prompts to install software.
- On the taskbar, click the Wi-Fi Settings icon

(48:00) • • • • • • 4:21 PM

• Click and highlight "Steelman\_PRO\_Video\_Scope" network



Wi-Fi Networks List

- Click the "Connect" button
- When prompted, enter the Wi-Fi network password, "00000000"
- Start the Steelman PRO Wi-Fi Video Scope application

### Using the Steelman PRO Wi-Fi Video Scope - Android, IPhone, and IPad

### **Camera Selection Page**

- Launch the Steelman PRO Wi-Fi Video Scope App
- From the "Camera" page, select "Steelman PRO Video Scope"



### **Camera Preview Page**

The camera preview page displays a real time picture of what the camera aimed at and also allows control over camera functions.



**Camera Preview Page** 

- To increase or decrease the size of the video scope image, press the 
  and 
  buttons
  To rotate the view of the video scope image, press the 
  and 
  buttons
- To fit the video scope image to your screen automatically, press the

NOTE: The picture size and position can also be adjusted by using pinch and drag finger actions on the touch screen of smart devices

button

To capture an image of what the camera is currently displaying, press the button. A message that the image was successfully saved will be displayed.
To record a video, press the button. The will flash GREEN and a recording message

will appear, along with a timer of the elapsed time of the recording. **REC** 00:07

• To return to the Camera Selection screen, press the  $\langle$  Back button.

### Viewing and Sharing Saved Images and Videos

Still images and videos that are taken during use of the Wi-Fi Video Scope are saved to a media gallery in the app. From the Media Gallery, these files can be viewed and shared with others.



Media Gallery

- To access the Media Gallery, click the button from the Camera Selection page.
- Select the "Steelman PRO Video Scope" from the Source List. Thumbnails of all saved items will be displayed.
- Tap on any file to view it. Tap and hold on the file to delete or share.



**Delete/Share Screen** 

- Press the back button to return to the Media Gallery
- To delete multiple files, press the Edit button. Select the checkbox of each file you wish to delete and press the Delete button.



### Software Settings

Several software functions can be modified using the Settings page. Additionally, customer support contact information can be found here.

- To access the settings page, click on the Settings button from the Camera Selection screen.
- The Auto Record Audio slider determines if the microphone will be activated or not during recording. To turn on the microphone, move the slider to right position. To turn off, move the slider to the left position.

Auto Record	Audio				
	100	100	23,752	 And a second	

Auto Record Audio Slider

• The Record Length selector determines the maximum amount of time per video that will be recorded. To increase or decrease the value, press the record button until the desired value is achieved.

Record 1 min		-	+	
	Record Length Selector			

• The About Us button gives useful information about the product, including contact information for customer service.

## Using the Steelman PRO Wi-Fi Video Scope - Windows

### **Camera Selection Page**

- Launch the Steelman PRO Wi-Fi Video Scope App
- From the "Settings" page, select Device "IP Camera:WifiVideoScope"



### Camera Preview Page

The camera preview area displays a real time picture of what the camera aimed at and also allows control over camera functions.

	eo scope		
A100 416			
	221		
2	Take Photo	Record Video	Ľ
Device Setting	Take Photo	Record Video	Ľ
Device Setting Device:	Take Photo	Photo Snap Setting Path: C:\Program Files (x86)\Steelman {	
Device Setting Device: Video Format:	Take Photo	Photo Snap Setting Path: C:\Program Files (x86)\Steelman Prefix: Snap_	
Device Setting Device: Video Format: Recording Method:	Take Photo IP Camera: WIFIVideoScope B00x600 V AVI (High Quality) V	Photo Snap Setting Path: C:\Program Files (x86)\Steelman Prefix: Snap_ Interval Snap	
Device Setting Device: Video Format: Recording Method: Video Renderer:	Take Photo IP Camera: WIFIVideoScope B00x600 V AVI (High Quality) Video mixing renderer 9 V	Photo Snap Setting Path: C: \Program Files (x86) \Steelman Prefix: Snap_ Interval Snap Interval Time: 1 ÷s	C
Device Setting Device: Video Format: Recording Method: Video Renderer: Video Compressor:	IP Camera: WIFIVideoScope         800x600         AVI (High Quality)         Video mixing renderer 9         Video mixing renderer 9         x264vfw - H.264/MPEG-4 AV(	Photo Snap Setting Photo Snap Setting Path: C: \Program Files (x86) \Steelman Prefix: Snap_ Interval Snap Interval Time: 1 ÷s Maximum: 100 ÷	
Device Setting Device: Video Format: Recording Method: Video Renderer: Video Compressor: Audio Device:	IP Camera: WIFIVideoScope         800x600         AVI (High Quality)         Video mixing renderer 9         Video mixing renderer 9         X264vfw -H.264/MPEG-4 AVC          Microphone (Realtek High Def	Photo Snap Setting Photo Snap Setting Path: C: \Program Files (x86) \Steelman Prefix: Snap_ Interval Snap Interval Time: 1 * s Maximum: 100 * Record Video Setting	
Device Setting Device: Video Format: Recording Method: Video Renderer: Video Compressor: Audio Device: Audio Compressor:	IP Camera: WIFIVideoScope         800x600         AVI (High Quality)         Video mixing renderer 9         Video mixing renderer 9         x264vfw - H.264/MPEG-4 AVK          Microphone (Realtek High Def          DCM	Photo Snap Setting Photo Snap Setting Path: C:\Program Files (x86)\Steelman [ Prefix: Snap_ Interval Snap Interval Time: 1 ÷ s Maximum: 100 ÷ Record Video Setting Path: C:\Program Files (x86)\Steelman []	E
Device Setting Device: Video Format: Recording Method: Video Renderer: Video Compressor: Audio Device: Audio Compressor:	IP Camera: WIFIVideoScope         B00x600         AVI (High Quality)         Video mixing renderer 9         Video mixing renderer 9         x264vfw - H.264/MPEG-4 AVK *         Microphone (Realtek High Def *)         PCM	Photo Snap Setting Photo Snap Setting Path: C:\Program Files (x86)\Steelman Prefix: Snap_ Interval Snap Interval Time: 1 ÷ s Maximum: 100 ÷ Record Video Setting Path: C:\Program Files (x86)\Steelman Prefix: Record_	

Camera Preview Page

- To view in full screen mode, click the 🚊 button
- To capture an image of what the camera is currently displaying, click the **Take Photo** button. The image will be saved to the Photos tab
- To record a video, press the 🔲 Record Video button. The video will be saved to the Videos tab.

### Viewing and Sharing Saved Images and Videos

- Videos and Photos can be viewed by going to the Photos or Videos Tab and clicking on the desired image or video.
- To print photos, click on the 📕 button
- To email photos, click on the 🕞 button
- To delete photos or videos, click on the file you wish to delete and then click the 💼 button

### Software Settings

Advanced users can modify camera settings on the Settings tab. Additionally, the location where pictures and video are stored can be changed on this tab

• To access the settings page, click on the 😵 settings tab.